

## Bode Plot Problem

### Problem

Given the following loop gain:

$$T(s) = \frac{A(1 + \frac{s}{\omega_1})}{(1 + \frac{s}{Q\omega_2} + \frac{s^2}{\omega_2^2})}$$

where

$$A = 50$$

$$\omega_1 = 150 \text{ rds/s}$$

$$\omega_2 = 8 \text{ rds/s}$$

$$Q = 3$$

Using asymptotic approximations only,

- Sketch the Bode magnitude and phase plots (~~on the following blank page~~). Be sure to label all break frequencies, slopes of sloping line, gains of sloping lines and gain and phase levels on zero slope lines.
- Find the maximum gain (as an absolute value) and the frequency or range of frequencies at which it occurs.
- Using your plots determine the phase margin and associated crossover frequency.
- Using your plots determine the gain margin and associated crossover frequency.
- Determine whether the closed loop system is stable.
- With the assumption that  $\omega_1$  may be moved, what value should it take to achieve a  $45^\circ$  phase margin.